

# OPERATION MANUAL

## BATTLE-LINK 1

## INSTALLING THE UNIT

The Battle-Link 1 can be installed in most common airsoft headgear setups. Stickers, velcro and clips are included in the package to allow for custom fitment. For a guide on the different installing methods, scan the QR code, or go to [battle-link.com/instructions](http://battle-link.com/instructions)



## OPERATION

**Power on/off** — Press the **Power & Mesh Button**

**Volume control** — Short press the **Minus** or the **Plus Button**.

**Check battery level** — Press and hold the **Minus Button**.

**Turn Mesh on/off** — Short press the **Mesh Button**.

While Mesh mode is on, The Battle-Link 1 will automatically connect to nearby Battle-Link users that are also in Mesh mode.

**Changing Mesh channels** — Press and hold the **Mesh Button** for 2 seconds, this will bring the unit in the channel settings. By pressing the **Mesh Button** once it will change the channel. Press and hold the **Mesh Button** again for 2 seconds and the channel settings will be saved. You can choose 1 - 10 channels.

**Reset Mesh settings** — Press and hold the **Mesh Button** for 5 seconds. This will clear all Mesh settings and put the unit back to channel 1 (default).

**Bluetooth intercom private mode** — Press and hold the **Power-** and the **Plus Button** simultaneously for 2 seconds, do this with both of the units that you want to connect in private mode. Short press one of the units **Power Button** to start searching for the others. Then press the **Power-** and the **Plus Button** once again to setup the

private intercom. To cancel the private intercom press the **Power Button** once.

Keep in mind that the private mode connection is a different protocol. With this connection type, the units will not use the Mesh connection. Therefore the connection strength can be different to the Mesh type.

## PAIRING WITH PHONE

Make sure the Battle-Link 1 is turned off, press and hold the **Power Button** for 5 seconds. After this the BL-1 will enter the pairing mode, the **LED Indicator** will flash red & blue. Turn on Bluetooth on your phone, navigate to the Bluetooth connection setup in your phone and select "T60R".

## PHONE OPERATION

**Answer a call** — Short press the **Power Button**.

**Cancel a call** — Short press the **Power Button**.

**Reject an incoming call** — short press the **Power Button** twice.

**Redial** — Short press the **Plus Button** twice.

**Voice dial** — Short press the **Minus Button** twice.

## MUSIC OPERATION

WHILE CONNECTED TO A PHONE

**Play/Pause music** — short press the **Power Button**.

**Last song** — Short press the **Power Button** twice.

**Next song** — Short press the **Minus Button** twice.

**Share your music with other users** — short press the **Power Button** twice while connected and while listening to music.

## FM RADIO

**Radio on/off** — Press and hold the **Plus-** and the **Minus Button** simultaneously for 2 seconds.

**Search upwards** — Short press the **Plus Button** twice while radio is on.

**Search downwards** — Short press the **Minus Button** twice while radio is on.

**Save current station** — Short press the **Power Button** twice when you find a station.

**Browse saved stations** — Short press the **Power Button** once.

